

# 28 GHz Gyrotron and 4.6 GHz Klystron Heating Options for LDX





P. P. Woskov<sup>1</sup>, A. C. Boxer<sup>1</sup>, J. L. Ellsworth<sup>1</sup>, D. T. Garnier<sup>2</sup>, J. Kesner<sup>1</sup>, M. E. Mauel<sup>2</sup>, P. C. Michael<sup>1</sup>

<sup>1</sup>Plasma Science and Fusion Center, MIT. Cambridge, MA, 02139 USA, <sup>2</sup>Department of Applied Physics, Columbia University, New York, NY 10027 USA

ABSTRACT - The success of fully levitated LDX plasma operations is now motivating increasing the plasma heating power to explore the full potential of high beta plasma stability in a dipole magnetic configuration. Adding 28 GHz gyrotron and 4.6 GHz klystron electron cyclotron heating using sources. available at MIT is being evaluated. A Varian model VGA-8050M 28 GHz gyrotron that is capable of 200 kW in 0.1 s pulses or 10 kW CW is on site, and the output of one 250 kW. 0.5 s klystron at the adjacent C-Mod site could be transmitted to LDX. Adding these sources would significantly increase maximum heating power above the present 15 kW maximum to access higher beta plasmas. Heating at 28 GHz in particular, would be above cutoff for plasma densities up to the 10<sup>13</sup> cm<sup>-3</sup> range which are presently not accessible with the current low power 2.45 to 10.5 GHz heating sources. Overmoded waveguides would be used for both 28 and 4.6 GHz to efficiently transmit the 100+ kW power levels into LDX to heat at the electron cyclotron fundamental and harmonics.

#### Introduction

High-power microwave heating sources available at MIT could be implemented with modest effort to increase LDX plasma density and pressure

So far successful levitated plasmas have been achieved with a maximum of 15 kW of microwave heating power

- 2.45 GHz magnetron, 2.5 kW
- 6.4 GHz klystron. 2.5 kW
- 10.5 GHz klystron, 10 kW

A 200 kW, 28 GHz gyrotron is currently located adjacent to LDX as shown above right, but needs to be made operational


- Requires high voltage power for the electron gun 80 kV 8 0 A for 200 kW 0.1s pulses
  - 40 kV, 0.87 A for 10 kW, CW
- A total of 1960 A current for 4 main coil and 2 gun coil magnets
- Cooling water connections for magnets, gyrotron collector, and body

A 3 MW, 4.6 GHz 12 klystron system is located a little over 100 m away at the C-Mod site

> -An efficient waveguide could bring power from one 250 kW klystron to LDX

The possible implementation of these additional sources of microwave heating to significantly increase LDX plasma performance are described and details of the waveguide transmission lines given

# 28 GHz Gyrotron Heating



One possible geometry for 28 GHz X-mode launched heating perpendicular to the magnetic field. The heating beam would be directed at the fundamental and 2<sup>nd</sup> harmonic electron cyclotron resonances.

#### Circular TEn2 Transmission Line Attenuation

The gyrotron output is mainly in the circular TE<sub>n2</sub> mode. A mode filter or converter will be used (not shown) if necessary to achieve a pure mode for transmission.

Assuming copper waveguide with a conductivity of 5.88 x 107 mhos/m, the TE<sub>02</sub> mode loss at 28 GHz for the transmission line components shown above are:

63 mm diameter	-0.004 dB/m	3.5 m	-0.014 dE
38 mm diameter	-0.021 dB/m	5.0 m	-0.105 dE
Two bends 38 mm dia.	-0.042 dB/m	3.2 m	-0.134 dE


The total ohmic transmission losses are calculated to be about 5% (-0.25 dB). It is reasonable to expect a transmission efficiency to the plasma of 90% allowing another 5% losses for the window and taper

### Many of the 28 GHz transmission components are available or easily fabricated.





## 4.6 GHz Klystron Heating



### Rectangular TE<sub>01</sub> / Circular TE<sub>11</sub> Transmission Line Attenuation

Simple Rectangular to Circular Transition http://www.ham-radio.com/sbms/techpapers/K6BLG/circ\_rect.html  $TE_{01} \square b \longrightarrow TE_{11} \nearrow$ 

Homogenous Transition, Cutoff Wavelengths Equal

WR-187, 47.55 x 22.15 mm ---- 55.73 mm dia.

Quarter Wavelength Matching Section

 $Z_{in} = \frac{2b}{1} = 0.932$   $Z_{out} = \frac{2r}{1} = 2$   $Z_{in} = \frac{2b}{1} = 1.365$ 

95% of quarter guide wavelength  $\frac{1}{4}\lambda_g = 22.37 \text{ mm}$ to account for

- Overmoded circular TE<sub>11</sub> for main 100 m waveguide run to reduce loss
- Fundamental rectangular WR-187 to negotiate bends at input and output
- · Aluminum tubing is proposed for the 100 m run to reduce costs

→ Al conductivity 2.50 x 10<sup>7</sup> mhos/m

100 mm dia. Al wg -0.004 dB/m -0.4 dB 100 m WR-187 -0.02 dB/m 30 m -0.6 dB

If another 0.5 dB loss is allowed for a total loss of 1.5 dB, then it may be possible to transmit up to 175 kW from one klystron to LDX


### Parabolic Circular Taper

J. L. Doane, Inter. J. Infrared & Millimeter Waves, 5, 737-751, 1984

### Taper Lengths for which Mode Conversion Vanishes

$$\begin{split} L_{\scriptscriptstyle n} &= \frac{K_{\scriptscriptstyle o} \left(a_2^2 - a_1^2\right)}{P_{\scriptscriptstyle o} \lambda} \Bigg[ \Bigg(\frac{n\pi}{K_{\scriptscriptstyle o} \ln \left(a_2/a_1\right)}\Bigg)^2 - 1\Bigg]^{\frac{1}{2}} \underbrace{a_{\scriptscriptstyle I}, a_2 \text{ input and output radii,}}_{a_{\scriptscriptstyle I} = 27.8 \text{ mm}, a_2 = 50 \text{ mm}} \\ &\text{for TE}_{11} - \text{TM}_{11} \text{ conversion } K_{\scriptscriptstyle O} = -0.65, \ P_{\scriptscriptstyle O} = 0.90 \end{split}$$

A taper length as short a 16 cm (n=1)




could be used but a length of 32 cm (n= 2) would be better because TE<sub>12</sub> mode conversion loses (not shown) would be lower at longer length. Other possible modes for conversion from TE<sub>11</sub> at 4.6 GHz do not propagate in

Parabolic Profile  $\longrightarrow a(z) = \sqrt{a_1^2 + 2Fz}$ 




### 137 GHz ECE Measurements


- A 137 GHz radiometer was installed to view ECE directed vertically downward from the high field region of LDX
  - max. LDX field is 3.25 Tesla on inside F-Coil - only harmonic emission observed at 137 GHz
- Radiometer noise temp. 3000 K with 3 GHz double side band
- 35 mm dia. 1.1 m long ceramic waveguide from radiometer to fused guartz window for HE11 mode launched field-of-view
  - 1.9 dB insertion loss
  - another 7.0 dB attenuator inserted to prevent radiometer saturation after initial observations
- Field of view at plasma ~0.3 m 1/e<sup>2</sup> dia. encompassing >12 harm. partially obstructed by F-Coil catcher (not shown)





Radiometer calibrated to window with liquid nitrogen black body





- At 137 GHz 500 eV equivalent black body signals are observed at the LDX bottom window
- This is a lower limit for the actual emission at the plasma since the plasma does not completely fill the view of the
- In F-coil supported discharges the 2.45 and 6.4 GHz sources do not produce significant hot electrons in view of the 137 GHz radiometer
- The presence of high energy electrons would make possible harmonic ECE heating at frequencies above 100 GHz

